

		15 AMPERE		20 AMPERE		30 AMPERE		50 AMPERE		60 AMPERE	
		RECEPTACLE	PLUG	RECEPTACLE	PLUG	RECEPTACLE	PLUG	RECEPTACLE	PLUG	RECEPTACLE	PLUG
2-POLE 2-WIRE	125V	B-6 ¹⁾ 1-15R ²⁾	B-6 1-15P								
	250V			B-6	B-6						
	277V					(RESERVED FOR FUTURE CONFIGURATIONS)					
	600V					(RESERVED FOR FUTURE CONFIGURATIONS)					
2-POLE 3-WIRE GROUNDING	125V	B-7, 16, 28 5-15R	B-16, 17, 28 5-15P	B-11, 13, 21-23, 16, 28 5-20R	B-16, 24, 28 5-20P	B-29 5-30R	B-29 5-30P	B-30 5-50R	B-30 5-50P		
	250V	B-16, 18, 28 6-15R	B-16, 19, 28 6-15P	B-16, 25, 28 6-20R	B-16, 26, 28 6-20P	B-29 6-30R	B-29 6-30P	B-30 6-50R	B-30 6-50P		
	277V AC	B-20 7-15R	B-20 7-15P								
	347V AC	B-13 24-15R	B-20 24-15P								
	480V AC					(RESERVED FOR FUTURE CONFIGURATIONS)					
	600V AC					(RESERVED FOR FUTURE CONFIGURATIONS)					
	125/250V			B-31 10-20R	B-31 10-20P	B-32 10-30R	B-32 10-30P	B-32 10-50R	B-32 10-50P		
	30 250V										
	30 480V					(RESERVED FOR FUTURE CONFIGURATIONS)					
30 600V					(RESERVED FOR FUTURE CONFIGURATIONS)						
3-POLE 4-WIRE GROUNDING	125/250V					B-33 14-30R	B-33 14-30P	B-33 14-50R	B-33 14-50P	B-33 14-60R	B-33 14-60P
	30 250V					B-34 15-30R	B-34 15-30P	B-34 15-50R	B-34 15-50P	B-34 15-60R	B-34 15-60P
	30 480V					(RESERVED FOR FUTURE CONFIGURATIONS)					
	30 600V					(RESERVED FOR FUTURE CONFIGURATIONS)					
	30Y 120/208V										
4-POLE 4-WIRE	30Y 120/208V			B-35 18-20R	B-35 18-20P			B-35 18-50R	B-35 18-50P	B-35 18-60R	B-35 18-60P
	30Y 277/480V					(RESERVED FOR FUTURE CONFIGURATIONS)					
	30Y 347/600V					(RESERVED FOR FUTURE CONFIGURATIONS)					
4-POLE 5-WIRE GNDG	30Y 120/208V					(RESERVED FOR FUTURE CONFIGURATIONS)					
	30Y 277/480V					(RESERVED FOR FUTURE CONFIGURATIONS)					
	30Y 347/600V					(RESERVED FOR FUTURE CONFIGURATIONS)					